




# SimplePack 4.0 Plus



## SimplePack 4.0 Plus

### ADVANCED EDITION

#### ADDITIONAL OPTIONS TO SIMPLEPACK 4.0 PLUS:

- Machine learning
- Barometer
- Gyroscope
- Pedometer
- Precise time
- Larger memory for WiFi precise location
- Even lower battery consumption for some use cases

[Please contact us with your inquiry and device requirements]

Typical battery life	10 years
Number of messages	30,000
Waterproof rating	IP68
Battery	1500 mAh
Length	81 mm
Thickness	12 mm
Width	29.5 mm
Volume	29 cm <sup>2</sup>
Weight	30g
Number of business use cases	over 50
WiFi sniffing for tracking	yes
Button	yes
LED	red
Temperature measuring range	-40 to 60°C / ± 0.5°C
Accelerometer	yes
Magnetometer	yes
Ambient light	yes
Reed switch	yes
Operating temperature	-40°C to 60°C
Supported radio zones	1,2,3,4,5,6
Sigfox Ready class	0U
Full IoT platform provided with trial period	yes
Any IoT platform can be used	yes
Programming	online, click and select, batch through downlink
Automation and workflow	Zapier, others in preparation
Fixtures for screws drill in and high tensile cable ties	optional
End customer packaging	optional, several ready options
Branding	optional, several ready options
Custom firmware	optional
Sigfox IoT Agency designed and tuned antenna	yes

Device	Sensors	Number of messages*
SimplePack 4.0 Basic	Button, accelerometer, LED, ambi temperature	10,000
SimplePack 4.0 Plus Button	Button, LED, ambi temperature	30,000
SimplePack 4.0 Plus Orientation and Motion	Button, accelerometer, LED, ambi temperature	30,000
SimplePack 4.0 Plus WiFi Tracker	Button, accelerometer, LED, ambi temperature, WiFi locator	30,000
SimplePack 4.0 Plus Precise Temperature	Button, accelerometer, LED, precise temperature	30,000
SimplePack 4.0 Plus Door eCompass	Button, accelerometer, LED, ambi temperature, magnetometer	30,000
SimplePack 4.0 Plus Magnetic Switch	Button, LED, ambi temperature, magnetic reed switch	30,000
SimplePack 4.0 Plus PoC	Button, accelerometer, LED, WiFi locator, precise temperature, magnetic reed switch, light sensor	30,000

other options available by use case upon request

\* Uplink messages in Guard me mode at default configuration. For more information please refer to the "battery longevity and levels" documentation at [ask.simplehw.eu](http://ask.simplehw.eu).

[www.simplehw.eu](http://www.simplehw.eu)

[#simplehw](https://twitter.com/simplehw)

[#simplepack](https://twitter.com/simplepack)

simple hw

simple things